

## Instructions

### Instructions for the Safety Supervisor HV

**Document ID:** [SDOK-515-55](#), revision: 4.0

**Confidentiality:** K0 Statnett open information, can be shared with everyone

This copy was downloaded 30.12.2022 by [Jon Halvor Holtet](#).

The original document may have been published in a new revision or revoked since this copy was downloaded.

The current revision of this document can be downloaded here:

<https://samhandling.statnett.no/styrendedok/Dok.aspx?id=SDOK-515-55&language=1033>

**Team:** [Elsikkerhet](#)

**Responsible:** [Jon Halvor Holtet](#)

**Document owner:** [Arnfinn Granheim](#)

**Verified:** 30.12.2022 by [Jon Halvor Holtet](#)

**Approved:** 30.12.2022 by [Arnfinn Granheim](#)

**Planned review by:** 30.12.2025

**Keywords:** El-sikkerhet

Based on the Norwegian document SDOK-515-11

## 1 Governing policy and legislation

These Instructions for the Safety Supervisor HV are subordinate to [policy sikkerhet](#) (Safety Policy). They are a supplement to, and superceded by [FSE 2006](#) (Safety regulations related to the maintenance and operation of electrical installations) which is pursuant to the "[Lov om tilsyn med elektriske anlegg og elektrisk utstyr](#)" (Act relating to the Inspection of Electrical Installations and Electrical Equipment).

## 2 Purpose and validity

The purpose of these Instructions is to ensure a high level of electrical safety during work on or in the vicinity of Statnett electrical installations and during their operation, by requiring adequate planning of all activities and the implementation of necessary safety practices to avoid any risk to life, health, or property.

This set of instructions applies to all high voltage installations where Statnett has operational responsibility. They are also valid for installations under construction and demolition, conducted under Statnett's responsibility where this has been agreed upon or described in writing.

## 3 Intended audience

All Statnett and external employees who are authorised Safety Supervisors HV in Statnett.

## 4 Definitions

**Switching Supervisor:** Person appointed to have responsibility for ensuring that all necessary switching operations in high voltage installations are conducted safely.

**Safety Supervisor HV (high voltage):** Person appointed to have responsibility for the electrical safety at the worksite.

**Safety Observer:** Person instructed and appointed by Safety Supervisor HV to supervise the work when Safety Supervisor HV has to leave the work site. The Safety Observer may/shall halt the work when necessary but is not allowed to restart the work or implement/remove safety measures.

**Operations Manager HV (high voltage):** Person appointed by the owner/manager to carry out and be responsible for the ongoing management and maintenance of electrical installations.

**Worksite:** Positions where personnel and equipment are inside the live working zone, or where there is a risk of entering the live working zone. The outer limit of live working zone is determined by the system voltage, cf. FSE § 5, table 1.

## 5 Safety Supervisor HV

5.1 Before being appointed, the Safety Supervisor HV must plan the work according to instructions/procedures and assess the need for a Safe Job Analysis (SJA).

- 5.2 Concerning work **on, or in the vicinity of, earthed and short-circuited installations**, before being appointed to a job, the Safety Supervisor HV must gain confirmation from the Switching Supervisor, that necessary de-energising, as well as labelling, re-energising prevention, inspection – MSI (Norwegian abbreviation), and terminal earthing, has been carried out.
- 5.3 The Safety Supervisor HV shall personally receive and written document appointment from the Switching Supervisor as Safety Supervisor HV specifically to each work task **on, or in the vicinity of, earthed and short-circuited installations**.
- 5.3.1 Before being appointed to a job, the Safety Supervisor must inform the Switching Supervisor about the number of portable earthing devices they plan to use.
- 5.3.2 After being appointed, the Safety Supervisor must inform the Switching Supervisor if the number of portable earthing devices used differs from what was planned.
- 5.4 The Safety Supervisor HV shall personally receive appointment from **the Local Area Manager**, or person with such authorization stated on the safety card ("UL"), for each specific work task **in the vicinity of energised installations**. Appointment must follow section 4.6 in [Electrical safety procedural works](#): Appointing Safety Supervisor HV for work on disconnected installations or in the vicinity of high voltage installations, and appointing Safety Supervisor LV for work on or in the vicinity of low voltage installations. Before work can begin, the Safety Supervisor HV must send notification in accordance with section 3.3 in [Electrical safety procedural works](#): Use of SMS notification by personnel in high voltage installations.
- 5.5 The Safety Supervisor HV shall personally receive appointment from **the Local Area Manager**, or person with such authorization stated on the safety card ("UL"), for each specific work task **for installations under construction or demolition**.
- 5.5.1 Internal Safety Supervisor HV must use section 4.6 in [Electrical safety procedural works](#): Appointing Safety Supervisor HV for work on disconnected installations or in the vicinity of high voltage installations, and appointing Safety Supervisor LV for work on or in the vicinity of low voltage installations.
- 5.5.2 External Safety Supervisor HV must use section 5.1 in [Electrical safety procedural works](#): Construction, demolition and removal of disconnected high voltage transmission lines and substations.
- 5.6 The Safety Supervisor HV is responsible for electrical safety associated with all work **on, or in the vicinity of, high voltage installations**, and must ensure that work is conducted in a safe manner in accordance with the applicable regulations and instructions/procedures.
- 5.7 The Safety Supervisor HV must personally explain his function to the rest of the team and give them necessary instructions about pending work. The Safety Supervisor HV must wear a safety vest or armband with the text "Leder for sikkerhet". The Safety Supervisor HV must be able to communicate directly with the team, without use of an interpreter or intermediary.
- 5.8 When working **on, or in the vicinity of, earthed and short-circuited installations (including installations under construction/demolition)**:
- 5.8.1 The Safety Supervisor HV must personally check that the installation at the worksite is not energised in accordance with section 4.4 in [Electrical safety procedural works](#): Voltage testing, and carry out necessary earthing and short-circuiting. Earthing and

- short-circuiting must be visible from the worksite<sup>1</sup>, or be located in a position where an equivalent degree of visibility is assessed to be achieved, based on a risk analysis<sup>2</sup>. The Safety Supervisor HV must personally check that all equipment used for voltage testing and earthing bears a valid sticker, and check that the equipment is in satisfactory condition in accordance with the user manual. Equipment must also be wiped dry if it is damp.
- 5.8.2 Concerning work on **transmission lines**<sup>3</sup>, it is mandatory to use 2 sets of earthing equipment. Their location must be chosen to eliminate any possibility of induced voltages and the risks this could cause to personnel, even if one of the earthing devices should fail. If it is possible to eliminate<sup>4</sup> any risk to personnel from induced voltages, and/or if a fixed earthing switch or manual earthing- and short-circuiting rod is used for earthing at the site of the work, only one earthing is required.
- 5.8.3 During voltage testing and setting up/removing temporary earthing<sup>5</sup>, at least **two persons must be present**. At least one of these must hold Safety Supervisor HV authorisation. Voltage testing must be carried out on site using voltage testing equipment. For the second person, an **independent access permit** (ref. [Instructions for training/access/safety cards to Statnett's electrical installations](#)) to the installation is required and the person must have a relevant trade certificate or relevant approval for the task by the Directorate for Civil Protection. Earthing equipment must be available at the site where voltage testing is being carried out. Earthing must be carried out directly after voltage testing.
- 5.8.4 The second person must contribute to and assist the Safety Supervisor in carrying out voltage tests and setting up/removing temporary earth or other earthing device, as planned. The second persons name must be documented by LfS in the duty journal/scribbling pad (transmission lines).
- 5.9 The Safety Supervisor HV must determine the correct safety distance and set up necessary protection and barriers at the site of the work.
- 5.10 The Safety Supervisor HV must instruct the rest of the work team in person and give them permission in person to start the job.
- 5.11 The Safety Supervisor HV must oversee the work or appoint and instruct a Safety Observer<sup>6</sup> to this task. Please refer to the applicable enclosure to these Instructions. The Safety Observer must wear a safety vest or armband with the text "Overvåker". The Safety Observer has limited authority and may not alter implemented safety measures. The Safety Observer can halt work if there is any uncertainty, but the work cannot start up again until the Safety Supervisor HV has checked the safety measures and given permission in person for work to restart.

---

<sup>1</sup> Visible from the worksite: It must be possible to observe the earthing visually. Status of the earthing can be communicated to the workteam by telephone or radio communication.

<sup>2</sup> An equalisation connection between work equipment and installation components can be used, in addition to the necessary earthing on-site to avoid electrostatic discharge through personnel in the event of strong induction.

<sup>3</sup> This includes work on lines under construction.

<sup>4</sup> Proof that there is no danger of induced voltages and associated risks must be documented with reference to procedures or by means of a risk analysis. If there is no risk of danger to personnel from induced voltages at the worksite, or if a distance from induced installation parts of more than four hundred millimetres can be maintained to both people and equipment, this must be documented. External parties must send information in the form of documentation to their employer at Statnett.

<sup>5</sup> Parallel connection of earthing equipment must be clarified with the supplier of the earthing equipment to obtain information about procedures and to establish the critical level in relation to short-circuit current.

<sup>6</sup> If the work that is going to be overseen is of electroprofessional character, the Safety Observer must have a relevant trade certificate or relevant approval for the task by the Directorate for Civil Protection.

In practice, this means the Safety Supervisor HV must give permission in person to start the work at the beginning of each day, having first checked the safety measures.

- 5.12 The Safety Supervisor HV must inform the person that appointed him if, for any reason, he cannot continue in the role of Safety Supervisor, and a new Safety Supervisor HV must be appointed. The former Safety Supervisor HV must inform the new Safety Supervisor HV of all safety measures that have been set up.
- 5.13 The Safety Supervisor HV is responsible for stopping all work if there is any risk of lightning.
- 5.14 The Safety Supervisor HV must ensure that all work stops if a drop in pressure is predicted in secured SF6- and DCB switches. Work can continue when the Safety Supervisor HV has received confirmation that conditions have improved sufficiently.
- 5.15 The Safety Supervisor HV must inform the rest of the team that the installation must be treated as energised when work has ceased. The Safety Supervisor HV must reverse/dismantle all safety measures and check that it is safe to re-energise the installation.
- 5.16 Concerning work **on, or in the vicinity of, earthed and short-circuited installations**, the Safety Supervisor HV must notify the Switching Supervisor in person that the installation is ready to be re-energised. This must be documented in writing, and shall be done without undue delay after the work has been completed.
- 5.16.1 The Safety Supervisor must also notify the Switching Supervisor of the number of portable earthing devices that have been removed.
- 5.17 Concerning work **in the vicinity of an energised installation**, the Safety Supervisor HV must report the work terminated in accordance with section 4.6 in [Electrical safety procedural works](#): Appointing Safety Supervisor HV for work on disconnected installations or in the vicinity of high voltage installations, and appointing Safety Supervisor LV for work on or in the vicinity of low voltage installations. In addition, the Safety Supervisor HV must send notification of this in accordance with section 3.3 in [Electrical safety procedural works](#): Use of SMS notification by personnel in high voltage installations.
- 5.18 Concerning work task **for installations under construction or demolition**, internal Safety Supervisor HV must report the work terminated in accordance with section 4.6 in [Electrical safety procedural works](#): Appointing Safety Supervisor HV for work on disconnected installations or in the vicinity of high voltage installations, and appointing Safety Supervisor LV for work on or in the vicinity of low voltage installations.

## 6 Abstinance from intoxicants

Persons appointed to be Safety Supervisor HV must agree to refrain from consuming alcohol or other intoxicants during the 8 hours prior to starting work.

## 7 Confirmation of compliance

The responsibility for checking compliance with instructions lies with the document holder and approving body.

The position of Operations Manager HV includes authority to draw up and approve work procedures, guidelines and instructions in areas covered by electrical safety in accordance with [policy sikkerhet](#) (Safety Policy – Norwegian document only).

## 8 Enclosures and references

Enclosure:

- Appendix to instructions

References:

- [Policy sikkerhet](#) (Safety Policy – Norwegian document only) (SDOK-856-6)
- [Instructions for the Switching Supervisor](#) (SDOK-515-54)
- [Instructions for earthing when replacing joints and/or cutting of conductors on transmission lines](#) (SDOK-515-58)
- [Instructions for the Safety Supervisor HV in case of Live Work](#) (SDOK-515-59)
- [Instruks for åpning av celledører i platekapslede høyspenningsanlegg](#) (Instruction for opening a celldoor in a sheet enclosed high voltage installation – only in Norwegian) (SDOK-515-17)
- [Instructions for the Safety Supervisor HV and clearing teams when clearing wooded areas near high voltage lines](#) (SDOK-515-57)
- [Instruction for connecting and disconnecting earth electrode installations](#) (SDOK-515-61)
- [Instruction for training/access/safety cards to Statnett's electrical installations](#) (SDOK-515-60)
- [Instruks for planlegging av arbeid i elektriske anlegg](#) (Instruction for planning of work in electrical installations – only in Norwegian) (SDOK-515-36)
- [Electrical safety procedural works](#) (SDOK-515-73)
- [Procedure for Safe Job Analysis \(SJA\)](#) (doc.no. 1609273 in IFS)
- [Safety regulations related to the maintenance and operation of electrical installations](#) (FSE 2006) (www.dsb.no)
- [Lov om tilsyn med elektriske anlegg og elektrisk utstyr](#) (Act relating to the Inspection of Electrical Installations and Electrical Equipment – only in Norwegian) (www.lovdatab.no)

## 9 Version log

Valid as of	Revision classification (New/Updated/Vocabulary/None)	Description of important changes
01.01.2023	Updated	Changed reference from Functional Policy Electrical Safety to Safety Policy. Changed reference from separately procedures to procedural works.

## **APPENDIX TO INSTRUCTIONS – APPOINTMENT OF SAFETY OBSERVER**

Number or date/time on work permit: .....

Short description of work operation:  
.....  
.....  
.....  
.....

I hereby declare that I have received instruction from the Safety Supervisor HV  
(name/block capitals):

.....  
with respect to the safety measures implemented, and that I have been made aware of the  
risks associated with working in the vicinity of a high voltage installation. I agree to comply  
with the instructions that I have received.

**Place:** ..... **Date:** .....

**Name (block capitals):** .....

**Signed:** \_\_\_\_\_

This declaration must be filed locally.

# Instructions

## Instructions for the Safety Supervisor HV

### Revision log SDOK-515-55:

Revision	Approved	Approved by	Description
4.0	<a href="#">Show changes</a> 30.12.2022	<a href="#">Arnfinn Granheim</a>	See the version log
3.0	<a href="#">Show changes</a> 29.12.2021	<a href="#">Arnfinn Granheim</a>	See the version log
2.0	<a href="#">Show changes</a> 29.12.2021	<a href="#">Arnfinn Granheim</a>	See the version log
1.0	<a href="#">Show changes</a> 08.12.2021	<a href="#">Arnfinn Granheim</a>	Migrated from IFS#1198675